

**Data Sheet** 

# **Remote Control**MP20A/MP20V Receiver

The MP20A/MP20V receiver is highly customizable with many features and mounting kits to ensure reliable and safe operation in potentially dangerous applications.

### **Features**

- Multiband radio with full-duplex communication
- External display for troubleshooting
- Removable EEPROM SIM module
- STOP: PLd, Category 3 according to EN ISO 13849-1:2008
- Multi-feedback capability
- 12 digital and 8 analogue outputs (PWM/Voltage)

## **Benefits**

- Highly field customizable
- Frequency management against interferences
- Easy and fast maintenance
- Suitable for all common proportional valves

# **Applications**

- Construction and mining vehicles and cranes
- Industrial vehicles
- Agriculture and forestry
- Maritime

Comprehensive technical literature is online at www.danfoss.com





# Technical data

Specification	MP20A	MP20V
Stop function	Cat. 3-PLd	
Ingress protection	IP65/NEMA4	
Frequency band	Multi-band (400-930 MHz)	
AC power supply	N/A	
DC power supply	9-35 Vdc	
Antenna	External/internal (default)	
Removable EEPROM	External	
Signaling	External	
ON/OFF outputs (maximum)	28	12
Analog outputs (maximum)	8 (PWM)	8 (Voltage)
CANopen	Yes	Yes
ON/OFF inputs (maximum)	24	
Analog inputs	5	
Maximum output current	2A	20mA
Working temperature range	-20° C to +70° C (-4° F to +158° F)	
Weight	1350 grams	
Dimensions	245 x 160 x 80	
Cable connection	Yes	
Associated transmitters	T70 2, T70 2 HALL, IK2, IK3, IK4	

Danfoss can accept no responsibility for possible errors in catalogues, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without subsequent changes being necessary in specifications already agreed.

All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.

2 | © Danfoss | May 2019 Al293282223764en-000201